

## 200m2 TV/Music Lounge Hearing Loop Kit

Part No. **AKT1**



### Overview

- Includes a PDA200E hearing loop amplifier, an AMP handheld microphone, an APXM outreach plate, an APL outreach plate and 2 x 6m Belden cable.
- Ideal for creating a high quality induction loop system for a TV or Music lounge.
- Wall-mountable PDA200E amplifier capable of driving a perimeter loop of up to 200m2.
- Internal drive, level and metal compensation controls.
- Two balanced / unbalanced line level inputs, one 100V line input and one microphone input with 12V phantom power for electret microphones.
- Full compatibility with the Outreach plate audio input extension system.
- Fully compliant with BS EN 60118-4 when correctly installed.
- Loop cable not included - our LOOP2W 1mm2 cable is suitable for most applications. If in doubt contact our technical department for advice



### More Information

### Technical Specifications

Type	Wall mounting. Requires fixed Mains wiring.
Coverage	200m2 approx.
Mains supply	230V 50/60Hz.
Auxiliary inputs	1 x Microphone, 2 x Line/Outreach and 1 x 100V line inputs via screw connectors.
Indicators	Input level; loop current meter (peak 3, 2, 1); compression; power on.



Controls	Input level; loop drive, metal compensation.
Product dimensions (mm)	W 228 x H 155mm x D 42mm (amplifier only).
Construction & finish	White painted steel (PDA200E); plastic accessories.
IP Rating	IP20.
Weight	1 kg (amplifier only).
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.
Kit contents	PDA200E hearing loop amplifier; AMP handheld microphone, APS SCART lead, APXM XLR mic. level connector plate, APL dual phono line level connector plate, AL5 lead; 2 x 6m Belden cable; Loop Fitted



T 01942 322744 E sales@c-tec.co.uk  
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom